

PCH-052 24V / 5 Amp

Automatic Battery Charger



Features

- Digitized readout of output volts and ampere.
- According to battery condition automatically to swap buck mode to float mode or vice versa, that improve charging efficiency and prolongs battery lifetime.
- The duration of the buck mode can be adjusted.
- Equipped with functions of short circuit and wrong polarity.
- Compact size and lighter than traditional type.
- Protection of reverse power comes from battery to charger.
- Force output can be done by a output trigger button.

Panel description

- | | |
|-------------------------------|---------------------------------|
| (1) DC output voltage readout | (5) DC output cable |
| (2) Float mode indicator | (6) Charger Activated indicator |
| (3) Buck mode indicator | (7) Fail to charge indicator |
| (4) Output Trigger button | (8) DC output current readout |

Specifications

- | | |
|--|--|
| ■ AC input power range : 80 ~ 250 VAC
Frquency : 50/60 Hz | ■ Default output voltage : float mode 26.6 VDC
buck mode 27.6 VDC |
| ■ DC Rated output power : 5 A @ 24 V | ■ Ambient Temperature : -20 °C ~ 60 °C |
| ■ Charging mode : Float or Buck mode | ■ Dimenssions : 138 mm x121 mm x198 mm |
| ■ Efficiency : greater than 75% at full load | ■ Weight : 1.2 kg |

Dimension

